

# Kiirjuhend adresseeritavale tulehäire paneelile iRIS4

## TULEHÄIRE

### TULEHÄIRE indikatsioon

#### Käivitatud sireenid

### TULEHÄIRE teade

### TULEHÄIRE tsoonides

The diagram shows three main sections of the fire alarm panel:

- TULEHÄIRE indikatsioon:** A list of indicators including HÄIRE (Alarm), EELHÄIRE (Pre-alarm), RIKE (Fault), SÜSTEEMI RIKE (System fault), VAIGISTATUD (Silenced), VIIDE (5), VÄLJA LÜLITATUD (Disarmed), TEST, and TOIDE (Power).
- TULEHÄIRE teade:** A screen showing the current alarm status, including the alarm type (Häire), the alarm zone (Tsoon), and the alarm address (Ahel).
- TULEHÄIRE tsoonides:** A grid showing the status of individual alarm zones (1-96).

## 1 TULEHÄIRE, sireenide viite seadistamine, tule- ja tulekaitse väljundid. Vaigista summer:

The screenshots show the fire alarm panel interface. The first screenshot shows the alarm status (Häire) and the alarm zone (Tsoon). The second screenshot shows the 'Vaigista summer' (Silence alarm) button, which is used to silence the alarm.

Juhul, kui on tegemist ühendatud paneelidega, siis sumeri vaigistamiseks vali:

The screenshots show the fire alarm panel interface. The first screenshot shows the 'Kõik' (All) button, which is used to silence all connected panels. The second screenshot shows the 'See' (This) button, which is used to silence only the selected panel.

The screenshots show the fire alarm panel interface. The first screenshot shows the 'Häire' (Alarm) button. The second screenshot shows the 'Tsoon' (Zone) button.

Mine tulehäire tekitanud tsooni ning kontrolli tulekahju olemasolu, seejärel järgi **Samm 2 – Alusta evakuatsiooni, ja/või** **Samm 3 – Lülita sireenid välja, vastavalt olukorrale.**

## 2 PÄRIS TULEHÄIRE, sireenide viite seadistamine, tule- ja tulekaitse väljundid. Alusta evakuatsiooni:

The screenshots show the fire alarm panel interface. The first screenshot shows the alarm status (Häire) and the alarm zone (Tsoon). The second screenshot shows the 'Evakueeri' (Evacuate) button, which is used to initiate evacuation.

Juhul, kui on tegemist ühendatud paneelidega, siis sumeri vaigistamiseks vali:

The screenshots show the fire alarm panel interface. The first screenshot shows the 'Kõik' (All) button, which is used to silence all connected panels. The second screenshot shows the 'See' (This) button, which is used to silence only the selected panel.

**Sireenid käivitunud → 112**

## 3 Lülita sireenid välja ja taasta:

The screenshots show the fire alarm panel interface. The first screenshot shows the 'Ligipääs 1' (Access 1) button. The second screenshot shows the 'OK' button.

The screenshots show the fire alarm panel interface. The first screenshot shows the 'Taasta' (Reset) button. The second screenshot shows the 'Ligipääs 2' (Access 2) button.

Juhul, kui on tegemist ühendatud paneelidega, paneel on taastatud normaalolekusse. Vajuta **LIGIPÄÄS 2**, ning seejärel **LOG OUT**.